

### Real-Time Monitoring

Real-time monitoring displays the air-flow, battery power, particle filter loading for the user.

### Intelligent Control

Respirator motor automatically adjusts the power and air-flow depending on the filter box loading.

### Various Filter Options

User can choose P3/gas/odor filter according to different applications and work environments.

### Triple-Alarm System

The warning light will flicker to indicate clogged filter or low battery, while the respirator will sound an alarm and vibrate.

### High-Performance Motor

High-quality brushless motor, strong air volume, low power consumption, ultra-quiet running and up to 3 times longer motors life.

### Airflow Indicator

### Battery Indicator

### ON / OFF Button

### Filter Warning

# CE 2834 EN 12941

Powered Air Purifying Respirator - Turbo Unit






## Product Specification

Air Flow Rate (Low speed)	170+lpm
Air Flow Rate (High speed)	210+lpm
Battery type	Rechargeable Li-ion battery
Charge time	1 hour
Battery life	At least 500 charges
Fast Charging Std Battery duration	9 hours at 170+lpm; 5-6 hours at 210+lpm
Fast Charging Heavy Dusty Battery duration	15 hours at 170+lpm; 9 hours at 210+lpm
Weight	1020g (Turbo Unit + Fast Charging Standard Battery)
Filter efficiency	>99.997%
Operating temp.	-5°C to 55°C
Storage temp.	-10°C to 55°C
Relative operating humidity (R.H.)	<90%
Relative storage humidity (R.H.)	<85%
Alarm	Audible, Visible, Vibration
Nominal Protection Factor (NPF)	500 for TH3 EN 12941

## Applications

- Spray Painting
- Chemical Treatment
- Powder Handling & Mixing
- Clean Room
- Laboratory

## Industries

-  Automotive
-  Chemical
-  Pharmaceutical
-  Heavy Engineering
-  Windmill Manufacturing

### Parts & Accessories

**CABM2000**  
PAPR Turbo Unit Body



**CA2101**  
Fast Charging Standard  
Lithium Battery



**CAP302**  
Particle filter (P3 filter)



**CAPF01**  
Pre-filter



**CASC01**  
Spark screen



**CAFC01**  
Filter cover



**CA2111**  
Fast-charging battery charger



**CABC01**  
Standard Waist Belt

### Packaging Information

TBD / Polybag

TBD / Carton

Carton Dimension - TBD

Carton Weight - TBD

### SKU Information

Product SKU	Size	Inner pack UPC	Carton GTIN
TBD	TBD	TBD	TBD



# ConAer™

## CA2100

### PAPR Configurations

**Turbo Unit**



**CA2100**  
 PAPR Turbo Unit Body

**Filter**



**CAP302**  
 Particle filter (P3 filter)



**CAGF01**  
 Gas Filter A2 with NFC Label



**CAGF02**  
 Gas Filter A1B1E1K1 with NFC Label



**CAOF01**  
 Odour Filter with NFC Label

**Battery & Charger**



**CA2101**  
 Fast Charging Standard Lithium Battery




**CA2102**  
 Fast Charging Heavy Duty Lithium Battery




**CA2111**  
 Battery Charger


**Breathing Tube & Sleeve**




**CABT01**  
 Standard Breathing Tube



**CABT02**  
 Quick Release Breathing Tube



**CABTCG**  
 FR Breathing Tube Cover



**CABTCW**  
 Breathing Tube Cover

**Belt**



**CASS01**  
 Shoulder Strap



**CABC02**  
 Standard Belt Cushion



**CABC01**  
 Standard Waist Belt




**CABC03**  
 High End Waist Belt (Flame Retardant)




**CABP01**  
 Turbo Unit Back Pack


**Hood / Face Shield & Welding Helmet**




**W400 Air**  
 Auto Darkening Welding Helmet




**W500 Air**  
 Flip-up Auto Darkening Welding Helmet



**HH500**  
 Hard Hood



**SH300**  
 Soft Hood with Shroud



**SH400**  
 Soft Hood with Long Shroud